

WiPort G Configuration Notice

Open HyperTerminal program

Set	Bits per second:	9600
	Data bits:	8
	Parity:	None
	Stop bits:	1
	Flow Control:	None

Keep press "x" key, plug in the USB cable to RS232 Module to power WiPort module and enter to Setup mode, click "Enter" key

0)	Server	
	Network Mode	1 (Wireless Only)
	IP	192.168.0.201 (or other)
	Set Gateway IP	Y
	Gateway IP	192.168.0.200
	Netmask: Number of bits for Host Part	8
	Change telnet config password	N
1)	Channel 1	
	Baudrate	115200
	I/F Mode	4C
	Flow	02
	Port No	10001
	ConnectMode	CC
	Dategram Type	01
	Remotw IP Address	0.0.0.0
	**** Use default ****	
2)	Channel 2	
	Baudrate	115200
	I/F Mode	4C
	Flow	02
	Port No	10002
	ConnectMode	CC
	Dategram Type	01
	Remotw IP Address	0.0.0.0
	**** Use default ****	
3)	***DO NOT CONFIGURE****	
4)	Wlan	
	Topology 0=Infrastructure, 1=Adhoc	0
	Network name (SSID)	dri
	Security 0=none, 1=WEP, 2=WPA	1(WEP)
	Authentication 0=Open/none, 1=shared	0
	Encryption 0=WEP64, 1=WEP128	1
	KEY	112233445566778899AABBCCDD
	TX Data rate 0=fixed, 1=auto	0
	TX Data rate 0=1, 1=2,2=5.5,3=11, 4=18, 5=24, 6=36, 7=54 Mbps	7 (11Mbps)